



FEATURES

The SKY Switch is a 2 button, one-touch control interface, designed specifically to work with the SKY 6LoWireless advanced lighting control solution.

- Can be individually programmed to control lighting zones or individual fixtures
- Can be mounted nearly anywhere
- Can easily control lights to be ON/OFF, press-and-hold for responsive dynamic dimming
- Use custom commands to call preset lighting scenes
- Perfect for offices, conference rooms, retail environments, warehouses, and other commercial spaces
- Works seamlessly with other SKY 6LoWireless products
- Fits standard Decora® wall plate
- Surface mount or standard wall box options
- Onboard indicator LED
- 5+ year battery life
- 6LoWPAN networked communication
- Available with battery or 24V input power

TECHNICAL SPECIFICATIONS

ELECTRICAL

2 Coin cell batteries or 9-28VDC input

Battery Life: 5+ Years

Switch Type: 2 Momentary Contact Switches

Trigger Actions: Long/short press/release

MECHANICAL

Dimensions: 2.6 X 1.25 X 0.4"

(66 X 32 X 10Mm)

Mounting:

Adhesive surface mount or wall box.

LED indicator for mesh connectivity

COMMUNICATIONS

Radio: 2.4 Ghz IEEE 802.15.4 with antenna diversity

Communications Protocol: 6LoWPAN


RPL Routing Configuration: Leaf

STANDARDS AND LISTINGS

Environment: -20°C to 60°C

FCC, Etc (pending)

CONFIGURATION OPTIONS



Gang Mount Wired
GM-W



Gang Mount Battery
GM-B



Surface Mount Battery
SM-B



For more information:

Nextek Power Systems Tel: (313) 887-1321
461 Burroughs Street Toll free: (877) 24-VOLTS
Detroit, Michigan 48202 Fax: (313) 887-9433
www.nextekpower.com info@nextekpower.com

